C: Type C D: Type D E: Type E

T-06B0152 T-0710139 T-0710140

Test switch (for EWH series only)

Test switch is stored under cover. Switch can be used to check the operation or adjust sound volume

EWH: 8 channels/bit input

EWHS: 1 channel

Rated Voltage 24: 12/24V AC/DC

48: 48V DC 100: 100V AC

EWH/EWHS

Signal Horn





32 sounds

IP65

NPN Open collector



Original wide horn featuring clear and high volume up to 105dB at 1m, designed for use in noisy environments.

- · 32 sounds are pre-recorded in one unit.
- · For enhanced durability and safety in the work environment.
- · Built-in Alarm: Adjustable audible sound up to 105dB at 1m with volume control.
- · Installation: Indoors—upright, inverted, sideways; Outdoors—upright only. (Do not install the horn facing upward).
- · Easy Installation: With anti-corrosive stainless steel mounting bracket.
- · NPN Compatible: 24V type only (EWH series only).
- · Conforms to the CE requirements (for 12V, 24V type).

Available by Special Order

• PNP open collector type.


EWH / EWHS Type

	Model	Rated Voltage	Voltage Range	Power Consumption	Volume	Outer Contact Capacity	Operating Temperature Range	Auxiliary Input	Channel	Protection	Mass
	EWH-24	12/24V AC/DC	8V~28V AC/9V~35V DC	8W	Max. 105dB at 1m		EW:	contact 8/1bit 32/binary			1.2kg
EWH	EWH-48	48V DC	35V~60V DC	10W					8/1bit or		1.2kg
EVVI	EWH-100	100V AC	90V~132V AC	12W					32/binary		1.4kg
	EWH-200	200V AC	180V~260V AC	13W		EW:					1.4kg
	EWHS-24	12/24V AC/DC	8V~28V AC/9V~35V DC	8W		10mA EWH/EWHS:	-20°C~+60°C		32/biriary] '
EWHS	EWHS-48	48V DC	35V~60V DC	10W			Humidity	EWHS:	,	IP53 IP65*	1.2kg
	EWHS-100	100V AC	90V~132V AC	12W			contact	'	11 00	1.4kg	
	EWHS-200	200V AC	180V~260V AC	13W		More than					1.4Kg


* By special order

Wiring Diagram

Dimensions



Signal wires (for EWH/EW series only)



Fuse capacity (FWH/FWHS)

EWHS

	,	
Model	Rated Voltage	Fuse
EWH-24/EWHS-24	12-24V	1A (Slow-blo
EWH-48/EWHS-48	48V	1A (Normal
EWH-100/EWHS-100	100V	1A (Normal
EWH-200/EWHS-200	200V	1A (Normal

8 (Blue) > 7 (Green) > 6 (Orange) > 5 (Red) > 4 (Lightgreen) > 3 (Pink) > 2 (Yellow) > 1 (Skyblue) The greater number has priority when any of the channels are activated simultaneously.

Polarity symbol of power source is for EWH and EWHS series, in 12/24V DC and 48V DC types.

Sound Selection Charts

32 sounds are pre-recorded in one unit. 4 sound types are available.

Dipswitch, volume and test switch are stored under cover *EWHS/EW does not have test switch

EW does not have dipswitch

EWH/EWHS-A			
Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Bell (clear high pitched bell)	Yelp (rapid siren)
Rapid Hi-Lo	Melody Chime	Synthesized Piano	Synthesized Bell
Stutter (rapid intermittent horn) Bell (clear high pitched bell)	Synthesized Melody Chime	Chime	Call sign
Fur Elise	Maiden's Prayer	Minuet	Annie Laurie
London Bridge is Falling Down	Holdiridia	Mary Had a Little Lamb	Camptown Races
Kuck kuck	Der Schmied im Walde	On the Bridge of Avignon	Daydream Believer
Amary ll is	Mozart Symphony No. 40	Itsy Bitsy Spider	Ich bin ein Musikante
Jeux Interdits	Katuscha	Grandfather's Clock	Ave Maria

EWH/EWHS-C

Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Bell (clear high pitched bell)	Yelp (rapid siren)	
Rapid Hi-Lo	Melody Chime	Synthesized Piano	Synthesized Bell	
Stutter (rapid intermittent horn) Bell (dear high pitched bell)	Synthesized Melody Chime	Chime	Ca ll sign	
Can't Take My Eyes off of You	Top of the World	The Entertainer	Amazing Grace	
Amairono Kamino Otome	Les Champs-Elysees	Canon	Rara Sanshain	
Uchuusenkan Yamato	Oshiete	Makenaide	Gonna Fly Now (Theme for 'Rocky')	
I Don't Want to Miss a Thing	Yozorano Mukou	Aiwa Katsu	Haruyo Koi	
Gattsudaze	Odoru Ponpokorin	Imasugu Kisu Mi	Truth	

EWH/EWHS-D

Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Bell (clear high pitched bell)	Yelp (rapid siren)
Rapid Hi-Lo	Melody Chime	Synthesized Piano	Synthesized Bell
Runner	Mamotte Agetai	Chime	Call sign
Oribiao Kikinagara	A September	Doyoubino Koibito	Akino Kehai
Saafu Tengoku Sukii Tengoku	Iro Howaitoburendo	Happy Birthday	Hi Ho
I've been working on the Railroad	Bear Song	Toys Go Cha Cha Cha	Konnako Irukana
Wiegenlied	Rudolph the Red-nosed Reindeer	She Wore a Yellow Ribbon	Oh My Darling Clementine
Yellow Rose of Texas	Yankee Doodle	When the Saints Go Marching In	Londonderry Air

EWH/EWHS-E

Beep (slow intermittent horn)	Stutter (rapid intermittent horn)	Inverted Receille	Annie Laurie
Stutter (rapid intermittent horn)	Synthesized Melody Chime	Galactic Motor	London Bridge is Falling Down
Bell (clear high pitched bell)	Chime	Ringing Phone	Mary Had a Little Lamb
Yelp (rapid siren)	Call Sign	Two Tone	Camptown Races
Rapid Hi-Lo	Train Ride	Alarm Clock	Amary ll is
Melody Chime	Galloping Hi-Lo	Ringing Hi-Lo	Mozart Symphony No.40
Synthesized Piano	Alien Chatter	Fur Elise	Ave Maria
Synthesized Bell	Falling Crystals	Minuet in G	Grandfather's Clock

PATLITE Corporation has not applied for permission to use certain copyrighted music or songs recorded in EWH/EWHS-A, C and D types outside of Japan. Therefore, please contact the local copyright association for permission before using the product in case this product is used outside of Japan. EWH/EWHS-E type is recommended for use outside of Japan as this model does not include copyrighted music or songs, and permission is